



4 STEREO ZONE AMPLIFIER 8Z50A



REMOTE CONTROL



FRONT VIEW



REAR VIEW

IDEAL HI-FI AMPLIFIER FOR HIGH END GYMNASIUMS, FINE DINING RESTAURANTS, CAFE'S AND HOMES

INPUTS: BUILT-IN FM RECEIVER, BUILT-IN USB READER, 2 AUX, OPTICAL, COAXIAL, 2 MICROPHONES & **BLUETOOTH**

OUTPUTS : SPEAKER OUTPUT FOR 8 CHANNELS, VARIABLE LINE OUTS TO CONNECT ACTIVE SUBWOOFER/ ADDITIONAL POWER AMPLIFIER

- POWER OUTPUT : 75 WATTS RMS/ CHANNEL @ 8 OHMS
- TOTAL HARMONIC DISTORTION : $\leq 0.5\%$
- INPUT IMPEDANCE : 47K
- INPUT SENSITIVITY : $\leq 300\text{mV}$
- FREQUENCY RESPONSE : 20Hz – 20KHz
- TREBLE ADJUSTMENT : $\pm 9.5 \text{ dB}$
- BASS ADJUSTMENT : $\pm 9.5 \text{ dB}$
- MIC SENSITIVITY : $\leq 20\text{mV}$
- AC POWER CONSUMPTION : 600 WATTS
- DIMENSIONS : 430 mm (W) X 265 mm (D)(including handles & sockets) X 90 mm (H)

Note: As part of our continuing programme to improve the design and quality of our products we shall be free to make changes in the design and specifications without any notice.