



PUBLIC ADDRESS AMPLIFIER PA 6Z360



REMOTE CONTROL



FRONT VIEW



REAR VIEW

- POWER OUTPUT – 360 WATTS
- BUILT-IN USB + FM RECEIVER + BT
- 3 MICROPHONE INPUTS WITH MIC 1 AS PRIORITY INPUT, MICROPHONE INPUTS HAVE ECHO, REPEAT & DELAY FUNCTIONS
- 2 AUX INPUT
- MASTER VOLUME, ACTIVE BASS & TREBLE TONE CONTROLS
- 6 ZONES OUTPUT WITH STEPPED VOLUME CONTROL FOR EACH ZONE
- PRE OUT AVAILABLE TO DAISY CHAIN AMPLIFIERS OR TO CONNECT AN ACTIVE SUBWOOFER
- TOROIDAL TRANSFORMERS FOR MAINS AND OUTPUT
- BRUSHED ALLUMINIUM ANODISED PANEL WITH ALLUMINIUM KNOBS OFFERING A RICH LUXURIOUS FINISH
- POWER SUPPLY : 230V, 50Hz
- TOTAL HARMONIC DISTORTION: $\leq 0.5\%$ @ 1KHz
- SENSITIVITY : 1/4" PHONE JACK(UNBALANCED) MIC 1 TO MIC 3 - 4mV
- AUX IN : 300mV
- LINE OUT : 650 mV - 750 mV
- FREQUENCY RESPONSE : 60 Hz - 20KHz +/- 3dB
- AC POWER CONSUMPTION : 720WATTS
- OUTPUT : 8 OHM, ALL 6 ZONES 100V OUTPUTS
- SIGNAL TO NOISE RATIO : > 80 dB
- VOICE PRIORITY MUTE : MIC 1
- TONE : BASS 100 Hz +/- 10 dB
TREBLE 10KHz +/- 10 dB
- DIMENSIONS: 483 mm(W) x 320 mm(D) x 88 mm(H)

Note: As part of our continuing programme to improve the design and quality of our products we shall be free to make changes in the design and specifications without any notice.