



# 4 STEREO ZONE AMPLIFIER 8Z100A



REMOTE CONTROL



FRONT VIEW



REAR VIEW

IDEAL HI-FI AMPLIFIER FOR HIGH END GYMNASIUMS, FINE DINING RESTAURANTS AND HOMES

INPUTS: BUILT-IN AM/FM RECEIVER, BUILT-IN USB + SD CARD READER, CD PLAYER, DVD PLAYER, MICROPHONE

OUTPUTS : SPEAKER OUTPUT FOR 8 CHANNELS, VARIABLE LINE OUT + VARIABLE RECORD OUT TO CONNECT ACTIVE SUBWOOFER/ ADDITIONAL POWER AMPLIFIER

- POWER OUTPUT : 100 WATTS RMS/ CHANNEL @ 8 OHMS
- TOTAL HARMONIC DISTORTION :  $\leq 0.5\%$
- INPUT IMPEDANCE : 47K
- INPUT SENSITIVITY :  $\leq 300\text{mV}$
- FREQUENCY RESPONSE : 20Hz – 20KHz
- TREBLE ADJUSTMENT :  $\pm 9.5 \text{ dB}$
- BASS ADJUSTMENT :  $\pm 9.5 \text{ dB}$
- LOUDNESS ADJUSTMENT : + 8 dB @ 50Hz, +4 dB @ 10KHz
- MIC SENSITIVITY :  $\leq 20\text{mV}$
- DIMENSIONS : 430 mm (W) X 450 mm (D)(including handles & sockets) X 90 mm (H)

Note: As part of our continuing programme to improve the design and quality of our products we shall be free to make changes in the design and specifications without any notice.