



# 4 STEREO ZONE AMPLIFIER 4MAX75

The DNM 4MAX75 is a 4 Stereo Zone Home Audio Amplifier having Multi Source/Multi Zone Matrix Routing that allows you to route any source to any specific zone(s).



Remote Control



Front View



Rear View

Inputs: BT, USB, Optical, Coaxial, AUX, FM and 2 mic inputs.

Outputs: 4 Stereo Speaker Zone Outputs, 4 Stereo Line Outputs(1 for each zone).

The controls are really easy to use. You can easily route any source to any zone(s) and select the volume levels for that zone from the unit or from the included remote. There is bass and treble EQ controls to customize the sound. The mic inputs have mic volume, mic bass, mic treble, echo, and delay controls making this perfect for Karaoke and PA announcements.

Applications: Multi Room Audio in Homes, Spa's, Offices, Restaurants, Bars, Places of Worship, etc. **Can also be used for Karaoke.**

POWER OUTPUT : 75 WATT RMS/CHANNEL @ 8 OHMS

MUSIC INPUT SENSITIVITY: 250mV/ 47K Ohm/ 1 KHz

MIC INPUT SENSITIVITY : ≤ 25mV

DIMENSIONS : 430mm(W) x 89mm(H) x 265mm(D)

AMPLIFIER FREQUENCY RESPONSE : 20Hz-20KHz

MIC FREQUENCY RESPONSE : 20Hz-20KHz

MIC EQ : Treble - +/- 10dB @ 10KHz, Bass - +/- 10dB @ 100 Hz

MUSIC EQ: Treble - +/- 10dB @ 10KHz, Bass - +/- 10dB @ 100 Hz

Note : As part of our continuing programme to improve the design and quality of all our products we shall be free to make changes in the design and specification without any notice.