



# PUBLIC ADDRESS AMPLIFIER PA 6240



FRONT VIEW



REMOTE CONTROL



REAR VIEW

- POWER OUTPUT – 240 WATTS
- BUILT-IN USB + FM RECEIVER + BT
- 3 MICROPHONE INPUTS WITH MIC 1 AS PRIORITY INPUT, MICROPHONE INPUTS HAVE ECHO, REPEAT & DELAY FUNCTIONS
- 2 AUX INPUT
- MASTER VOLUME, ACTIVE BASS & TREBLE TONE CONTROLS
- CHIME FUNCTION FOR ANNOUNCEMENTS AND SIREN FUNCTION FOR EMERGENCY HUMAN EVACUATION
- 6 ZONES OUTPUT WITH STEPPED VOLUME CONTROL FOR EACH ZONE
- AUX OUT AVAILABLE TO DAISY CHAIN AMPLIFIERS OR TO CONNECT AN ACTIVE SUBWOOFER
- TOROIDAL TRANSFORMERS FOR MAINS AND OUTPUT
- BRUSHED ALLUMINIUM ANODISED PANEL WITH ALLUMINIUM KNOBS OFFERING A RICH LUXURIOUS FINISH

- POWER SUPPLY : 230V, 50Hz
- TOTAL HARMONIC DISTORTION:  $\leq 0.3\%$  @ 1KHz
- SENSITIVITY : 1/4" PHONE JACK(UNBALANCED)  
MIC 1 TO MIC 3 - 0.5mV @ 600 OHM
- AUX IN : 650mV
- LINE OUT : 1V
- FREQUENCY RESPONSE : 50 Hz - 18KHz +/- 3dB
- AC POWER CONSUMPTION : 480WATTS
- OUTPUT : 8 OHM, ALL 6 ZONES 100V OUTPUTS
- SIGNAL TO NOISE RATIO : >85 dB
- VOICE PRIORITY MUTE : MIC 1
- TONE : BASS 100 Hz +/- 10 dB  
TREBLE 10KHz +/- 10 dB
- DIMENSIONS: 480 mm(W) x 340 mm(D) x 90 mm(H)

Note: As part of our continuing programme to improve the design and quality of our products we shall be free to make changes in the design and specifications without any notice.