

PACE

4 STEREO ZONE AMPLIFIER 4Z50 MPA



FRONT VIEW



REMOTE CONTROL
FOR MUSIC PLAYER
MODULE



REAR VIEW

INPUTS : BUILT-IN FM RECEIVER, BUILT IN USB CARD READER, AUX INPUT, EXTERNAL LINE INPUT TO CONNECT CD/DVD PLAYER

OUTPUTS : SPEAKER OUTPUTS FOR 8 CHANNELS, FIXED LINE OUTPUT TO DAISY CHAIN AMPLIFIER AND A VARIABLE OUTPUT TO CONNECT ACTIVE SUBWOOFER

- POWER OUTPUT : 30 WATT RMS/CHANNEL @ 8 OHMS /40 WATT RMS/CHANNEL @ 4 OHMS (Preferable to use @ 8 ohms only)
- TOTAL HARMONIC DISTORTION : $\leq 0.5\%$
- INPUT IMPEDANCE : 47K
- INPUT SENSITIVITY : ≤ 300 mV
- MIC INPUT SENSITIVITY : ≤ 20 mV
- FREQUENCY RESPONSE : 20Hz-20KHz
- TREBLE ADJUSTMENT : ± 9 dB
- BASS ADJUSTMENT : ± 9 dB
- DIMENSIONS : 430 mm(W) x 380 mm(D) x 75 mm(H)

THIS AMPLIFIER IS IDEALY USED FOR MULTI ROOM/ZONE BACKGROUND MUSIC APPLICATIONS IN GYMNASIUMS, FINE DINING RESTAURANTS & HOMES

Note: As part of our continuing programme to improve the design and quality of our products we shall be free to make changes in the design and specifications without any notice.